

TRANSISTOR NUMBER	PM OALT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
BF501	PS	T0106	L18	30V	30V	3V	20MA	125C	200MWF	200M	OR7	30/90	1MA	ULA	SGB			1
BF506	PS	T092	L74	40V	35V	4V	30MA	150C	250MWF	250M	1P2	20MN	3MA	VLG	ATB	BF414		1
BF509	PS	T092	L74	40V	35V	4V	30MA	150C	250MWF	400M	1P2	35MN	3MA	VLA	ATB	BF414		1
BF516	PS	T072	L06	40V	35V	4V	20MA	175C	150MWF	500M	OR5	25MN	3MA	ULA	ATB	BF576		1
BF523	NS	X10	L19	45V	45V	8V	50MA	150C	625MWF	100M	4P	600MN	10MA	ALN	TID	BC107C		0
BF540	PS	X10	L19	50V	45V	5V	50MA	150C	250MWF	90M	1R	60MN	1MA	FRH	TIW	BF440		1
BF541	PS	X10	L19	50V	45V	5V	50MA	150C	250MWF	90M	1R	45MN	1MA	RLG	TIW	BF440		1
BF542	PS	X10	L19	50V	45V	5V	50MA	150C	250MWF	90M	1R	30MN	1MA	RLG	TIW	BF451		1
BF576	PS	T092	L21	20V	15V	5V	50MA	150C	360MWF	800M		50/400	10MA	ULG	TIB	BSW25	2N4209	1
BF576TO5	PS	T092	L54	20V	15V	5V	15MA	150C	200MWF	800M	4R	30MN	10MA	ULG	TIB	BF576		2
BF594	NS	T092	L58	30V	20V	5V	30MA	150C	250MWF	130M	1R2	65/220	1MA	FRH	TIB	BF184		0
BF594	NS	X10	L19	35V	25V	5V	30MA	150C	250MWF	130M	1R2	65/220	1MA	RLA	TIB	BF184	2N3983	0
BF595	NS	T092	L58	30V	20V	5V	30MA	150C	250MWF	130M	1R2	35/125	1MA	FRM	TIB	BF185		2
BF595	NS	X10	L19	35V	25V	5V	30MA	150C	250MWF	130M	1R2	35/125	1MA	RLA	TIB	BF184	2N3983	0
BF596	NS	T092	L58	40V	30V	4V	30MA	150C	360MWF	200M	OR4	26MN	4MA	TIG	TIB	BF167		2
BF597	NS	T092	L58	40V	25V	4V	30MA	150C	360MWF	275M	OR6	38MN	7MA	TIA	TIB	BF173		2
BF597A	NS	T092	L58	40V	25V	5V	25MA	150C	360MWF	350M	OR5	40/90	7MA	TIA	TIB	BF173		1
BF597B	NS	T092	L58	40V	25V	5V	25MA	150C	360MWF	350M	OR5	40/90	7MA	TIA	TIB	BF173		1
BF606	PS	T092	L73	25V	25V	3V	25MA	150C	300MWF	600M	DP85	60MN	5MA	ULA	SID	BF272A	2N4959	2
BF622	NS	X90A	X90	250V	250V	5V	100MA	150C	1WH	60M	1R6	50MN	25MA	TVE	MUB			2
BF623	PS	X90A	X90	250V	250V	5V	100MA	150C	1WH	60M	1R6	50MN	25MA	TVE	MUB			2
BF639	PS	T072	L51	30V	25V	4V	30MA	200C	100MWF	700M	1P	15MN	2MA	ULG	TIF		2N3546	1
BF640	PS	T072	L51	30V	25V	4V	30MA	200C	100MWF	400M	OR5	15MN	2MA	ULG	TIF		2N3546	1
BF657	NS	T039	L04	160V	160V	5V	200MA	200C	7WC	50M	5P	25MN	30MA	TVM	ATB	BF257		1
BF658	NS	T039	L04	250V	250V	5V	200MA	200C	7WC	50M	5P	25MN	30MA	TVM	ATB	BF258		1
BF659	NS	T039	L04	300V	300V	5V	200MA	200C	7WC	50M	5P	25MN	30MA	TVE	ATB	BF259		1
BF666	NS	X17	L31	200V	150V	5V	1A	150C	2WC	100M	12P	40MN	10MA	RME	MOB	BF259	2N4927	2
BF667	NS	X17	L31	200V	150V	5V	1A	150C	2WC	100M	12P	40MN	10MA	RME	MOB	BF259	2N4927	2
BF668	NS	X17	L31	300V	250V	1A	150C	150C	2WC	100M	12P	40MN	10MA	RME	MOB	BF259	2N4927	2
BF679	PS	X37	L82	40V	35V	3V	30MA	150C	170MWF	700M	1P	25MN	3MA	TUG	ATB			1
BF679M	PS	X37	L82	40V	35V	3V	30MA	150C	170MWF	700M	1P	25MN	3MA	TUG	ATB			1
BF679S	PS	X63A	X63	40V	35V	3V	30MA	150C	160MWF	550M	1P	25MN	3MA	ULA	SID			2
BF680	PS	X37	L82	40V	35V	3V	30MA	150C	170MWF	400M	1P	35MN	3MA	TUM	ATB			1
BF689	NS	T072	L06	25V	15V	2V5	25MA	200C	200MWF	500M		20/150	2MA	ULA		BFX73	2N3839	2
BF689K	NS	T092	L73	25V	15V	3V5	25MA	200C	200MWF	900M	OP8	20MN	2MA	ULA	SID	BFX73	2N3839	2
BF694	NS	T092	L58	45V	30V	4V	50MA	150C	360MWF	200M	OR9	37MN	7MA	VLA	TIB	BF254		1
BF694A	NS	T092	L58	45V	30V	4V	50MA	150C	360MWF	200M	OR9	37MN	7MA	VLA	TIB	BF254		1
BF694B	NS	T092	L58	45V	30V	4V	50MA	150C	360MWF	200M	OR9	78MN	7MA	VLA	TIB	BF254		1
BF706	PS	T092	L14	30V	25V	3V	20MA	150C	350MWF	300M	1P2	20/120	2MA	VLG	MOB			1
BF709	PS	T092	L14	30V	30V	3V	20MA	150C	625MWF	350M	1P4	20MN	2.5MA	VLA	MOB			1
BF739	PS	T092	L14	20V	20V	3V	20MA	150C	350MWF	600M	1P4	20MN	2.5MA	ULG	MOB			1
BF740	PS	T092	L14	20V	20V	3V	20MA	150C	350MWF	600M	1P2	20MN	2MA	ULA	MOB			1
BF757	NS	X17	L31	250V	250V	6V	500MA	150C	2WF	45M	30R	40/180	30MA	RME	MOB	BF659	2N5058	2
BF758	NS	X17	L31	300V	300V	6V	500MA	150C	2WF	45M	30R	40/180	30MA	RME	MOB	BF659	2N5058	2
BF759	NS	X17	L31	350V	350V	6V	500MA	150C	2WF	45M	30R	40/180	30MA	RME	MOB	BF659	2N5058	2
BF760	PS	X17	L31	250V	250V	6V	500MA	150C	2WF	20M	3R	40/180	30MA	RME	MOB	BFT44	2N5416	2
BF761	PS	X17	L31	300V	300V	6V	500MA	150C	2WF	20M	3R	40/180	30MA	RME	MOB	BFT44	2N5416	2
BF762	PS	X17	L31	350V	350V	6V	500MA	150C	2WF	20M	3R	40/180	30MA	RME	MOB			2
BF779	PS	X41	L84	30V	25V	4V	20MA	125C	150MWF	400M	1P	20MN	2MA	ULG	TIW			1
BF780	PS	X41	L84	25V	20V	4V	20MA	125C	150MWF	350M	1P2	20MN	2MA	ULG	TIW			1
BF906	PS	T092	L15	30V	25V	3V	50MA	150C	350MWF	200M	1P2	20/120	2MA	VLA	TIB	BF706	2N4959	2
BF936	PS	T092	L74	30V	20V	4V	25MA	150C	250MWF	175M		25MN	1MA	RLA	MOB	BF451	2N3279	2
BF939	PS	T092	L06	30V	20V	4V	25MA	150C	250MWF	175M		25MN	1MA	RLA	RTC	BF451		2
BF967	PS	X37	L06	30V	30V	3V	20MA	150C	160MWF	700M	DP45	16/60	3MA	ULA	VAL	BF679M		2
BFAP15	NS	T072	L51	30V	30V	4V	30MA	175C	150MWF	150M	OP7	40/165	1MA	FRM	UNR	BF215		2
BFAP57	NS	T039	L04	160V	160V	5V	100MA	175C	5WC	40M	5P	25MN	30MA	TVM	UNR	BF257	2N3440	2
BFAP58	NS	T039	L04	250V	250V	5V	100MA	175C	5WC	40M	5P	25MN	30MA	TVE	UNR	BF258	2N3440	2
BFAP59	NS	T039	L04	300V	300V	5V	100MA	175C	5WC	30M	5P	25MN	30MA	TVE	UNR	BF259	2N3439	2
BFAP80	NS	T072	L06	30V	20V	3V	20MA	175C	150MWF	335M	DR56	15MN	2MA	TUG	UNR	BF180		2
BFAP83	NS	T072	L06	25V	20V	3V	15MA	175C	150MWF	400M	DR66	10MN	3MA	TUG	UNR	BF183		2
BFE214	NS	X12		30V	30V	4V	30MA	125C	150MWF	150M	OP7	90/330	1MA	FRH	UNR	BF184		2
BFE215	NS	X12		30V	30V	4V	30MA	125C	150MWF	150M	OP7	35/165	1MA	FRM	UNR	BF185		2
BFJ17	NS	T039	L04	40V	40V	5V	1A	185C	800MWF		12P	20MN	500MA	AMG	RIZ	BFY50	2N2297	2
BFJ18	NS	T072	L06	30V	30V	5V	100MA	200C	175MWF		OR6	20MN	2.5MA	RLA	RIZ	BF181	2N4252	2
BFJ19	NS	T072	L06	30V	30V	5V	100MA	185C	175MWF		OR6	22MN	2.5MA	RLA	RIZ	BF181	2N4252	2
BFJ45	NS	T039	L04	35V	35V	5V	1A	200C	800MWF		18P	40MN	150MA	AMG	RIZ	BFY50	2N2297	2
BFJ46	NS	T039	L04	35V	35V	5V	1A	200C	800MWF		18P	100MN	150MA	AMG	RIZ	BFY50	2N2297	2
BFJ47	NS	T039	L04	80V	80V	6V	1A	200C	800MWF	1A	15P	100MN	150MA	AMH	RIZ	BSW66	2N4001	2
BFJ48	NS	T039	L04	80V	80V	6V	1A	200C	800MWF		15P	40MN	150MA	AMH	RIZ	BSW66	2N4001	2
BFJ49	NS	T039	L04	64V	64V	6V	1A	200C	800MWF		18P	100MN	150MA	AMG	RIZ	BFY50	2N2297	2
BFJ50	NS	T039	L04	64V	64V	6V	1A	200C	800MWF		18P	40/120	150MA	AMG	RIZ	BFY50	2N2297	2
BFJ57	NS	T039	L04	125V	125V	5V	250MA	200C	800MWF		12P	30/150	30MA	AME	RIZ	BSW62	2N5082	2
BFJ64	PS	T039	L04	40V	40V	5V	500MA	200C	700MWF		10P	80MN	10MA	AMG	RIZ	BF595	2N4036	2
BFJ70	NS	T072	L06	25V	25V	3V	25MA	185C	175MWF		DR27	35MN	7MA	TIA	RIZ	BF173	2N3662	2
BFJ72	NS	T018	L01	45V	45V	5V	100MA	185C	500MWF	50M	8P	30/90	1MA	RLA	RIZ	BSW26	2N759	2