

A

A....	...-P	→2SA....., z.B./e.g. "A748" = 2SA748	Japantypen		
A....	...-P	→KSA....., z.B./e.g. "A 709"=KSA 709	Samsung		
A....	...-P	→KTA....., z.B./e.g. "A 940"=KTA 940	KEC		
A 14 A....U	Si-Di	Gl, contr.av., 25....1000V, 1A	31a	BYW 95 C	31a
A 15 A....U	Si-Di	Gl, 25....800V, 3A	31a	RGP 30 M	31a
A16-H010....H012	Si-Di	→SSi A16-H010...H012	31a	-	
A19-H025....H034	Si-Di	→SSi A19-H025...H034	31a	-	
A 202 D	LIN-IC	A/W-Verst. + ALC f. Recorder	16-DIP	TDA 1002 A	16-DIP
A 205 D	LIN-IC	NF-E, 20V, 2,2A, >4,5W(15V/4Ω)	12-DIP+a	TBA 810 AS	12-QIP+a
A 205 K	LIN-IC	=A 205D: +Kühlkörper/heat sink	12-DIP+a°	(TBA 810 AS)	12-QIP+a
A 208 E,K	LIN-IC	NF-E, 3W		(TBA 810)	
A 210 E	LIN-IC	NF-E, 20V, 2,5A, >5W(15V/4Ω)	12-DIP+a	TBA 810 AS	12-QIP+a
A 210 K	LIN-IC	=A 210E: +Kühlkörper/heat sink	12-DIP+a°	(TBA 810 AS)	12-QIP+a
A 211 D	LIN-IC	NF-E, 15V, 1A, 1W(9V/8Ω)	14-DIP	-	
A 220 D	LIN-IC	TV-Ton-ZF + NF-V	14-DIP	TBA 120 S	14-DIP
A 223 D	LIN-IC	TV-Ton-ZF + NF-V + VC-Signal	14-DIP	-	
A 224 D	LIN-IC	→TBA 120T	16-DIP	TBA 120 T	16-DIP
A 225 D	LIN-IC	FM-ZF, Dem., AFC	18-DIP	-	
A 230 D	LIN-IC	CTV-RGB-Matrix	16-DIP	-	
A 231 D	LIN-IC	CTV-RGB-Matrix	16-DIP	-	
A 232 D	LIN-IC	CTV-RGB-Matrix	16-DIP	TDA 2532	16-DIP
A 240 D	LIN-IC	TV-Video-ZF + AGC (PNP-Tuner)	16-DIP	TDA 440 S	16-DIP
A 241 D	LIN-IC	CTV-Video-ZF + AFC + AGC (PNP-Tuner)	16-DIP	TDA 2541	16-DIP
A 244 D	LIN-IC	AM-Empfänger/receiver	16-DIP	-	**
A 250 D	LIN-IC	TV-HA-Synchr. (f. Transistor-E)	14-DIP	TBA 950:2	14-DIP
A 252 D	LIN-IC	TV-HA-Synchr. (f. Thyristor-E)	14-DIP	-	
A 255 D	LIN-IC	TV-Horiz. + Vertik.-Synchr. + Osc.	16-DIP	TDA 2593	16-DIP
A 270 D	LIN-IC	CTV, Video-Signal	16-DIP	-	**
A 273 D	LIN-IC	2x NF-Stereo-Potentiometer (Vol.+Bal.)	16-DIP	-	**
A 274 D	LIN-IC	NF-Klangreg./AF DC tone-control	16-DIP	-	**
A 277 D	LIN-IC	LED-Display-Encoder, 12 LED	18-DIP	-	
A 281 D	LIN-IC	AM/FM-ZF	14-DIP	-	
A 283 D	LIN-IC	AM-V, AM/FM-ZF+NF, >0,3W(5.5V/8Ω)	16-DIP	TDA 1083	16-DIP
A 290 D	LIN-IC	PLL-MPX-Stereo-Decoder	14-DIP	-	**
A 295 D	LIN-IC	CTV-SECAM-Schalter/switch	16-DIP	-	
A 902 D	LIN-IC	Schwellwertschalter/threshold switch	4-DIP	-	
A 910 D	LIN-IC	Transistorkombination f. Camera	14-DIP	-	
A 1524 D	LIN-IC	→TDA 1524A	18-DIP	TDA 1524 A	18-DIP
A 1670 V,V1	LIN-IC	→TDA 1670(A)	15-SQL	TDA 1675 A	15-SQL
A 1818 D	LIN-IC	Recorder-A/W-Verst. + ALC	20-DIP	-	
A 2000 V	LIN-IC	2x NF-E, 28V, 2,5A, 2x>2,8W(9V/2Ω)	11-SQL	TDA 2005	11-SQL
A 2005 V	LIN-IC	2x NF-E, 28V, 3,5A, 2x>9W(9V/2Ω)	11-SQL	TDA 2005	11-SQL
A 2014 DC	LIN-IC	Video signalumschalter/video sign. sw.	8-DIP	TEA 2014(A)	8-DIP
A 2030(H,V)	LIN-IC	NF-E, ±18V, 3,5A, >16W(±14V/4Ω)	17/5Pin	TDA 2030	17/5Pin
A 3048 DC	LIN-IC	IR-FB-Empfänger/receiver	16-DIP	TDA 3048(A)	16-DIP
A 3501 D	LIN-IC	CTV-RGB + Video-E	28-DIP	TDA 3501	28-DIP
A 3510 D	LIN-IC	CTV-PAL-Decoder	24-DIP	TDA 3510	24-DIP
A 3520 D	LIN-IC	CTV-SECAM-Decoder	28-DIP	-	**
A 4100 D	LIN-IC	AM-Radio, FM-ZF	22-DIP	-	
A 4510 D	LIN-IC	→TCA 4510	18-DIP	-	
A 4511 D	LIN-IC	→TCA 4511	18-DIP	-	
A 4555 DC	LIN-IC	→TDA 4555	28-DIP	TDA 4555	28-DIP
A 4565 DC	LIN-IC	→TDA 4565	18-DIP	TDA 4565	18-DIP